

## P3000 PowerSmart Series™ Inverter Generator



The P3000 PowerSmart Series™ Inverter Generator by Briggs & Stratton takes portable power generation to the next level. Inverter technology makes it safer for sensitive electronics and computer controlled technology supplies smooth, steady power – and adjusts engine speed accordingly to suit your power needs and save fuel. Twin cushioned carrying handles or a retractable handle and wheels make it easy to move. Plus the on-board LCD StatStation® display keeps you informed about power use, run time and maintenance reminders. Now that's smart power.

- Easy starting, long life overhead valve engine – from a brand you can trust
- StatStation® LCD Display
- Parallel connector port – double your power output (when using optional kit to join two sets together)
- Inbuilt fuel gauge
- USB charging port
- Overload alarm, circuit breaker and low oil protection
- 2 x 240 volt outlets with weather protection
- 1 x 12 volt DC power accessory socket
- 'Peace of mind' with 3 year limited warranty and a National network of parts and service agents



### P3000 SPECIFICATIONS

<b>Engine Brand</b>	Briggs & Stratton	<b>Noise Level @ 7M dB(A)</b>	58 dBA
<b>Muffler</b>	Standard	<b>Volts</b>	240
<b>Watts – Starting</b>	3,000	<b>Watts – Running</b>	2,600
<b>Start Type</b>	Recoil	<b>Engine Series</b>	4-Stroke
<b>Engine Displacement (cc)</b>	171	<b>Run Time @ ½ Load</b>	Up to 5 Hours
<b>Fuel Tank Capacity</b>	5.7Ltr	<b>Fuel Gauge</b>	Yes
<b>Low Oil Pressure Protection</b>	Yes	<b>Weight</b>	44 kg
<b>Length with Wheels</b>	66 cm	<b>Width with Wheels</b>	36 cm
<b>Height with Wheels</b>	53 cm	<b>Wheel Diameter</b>	15 cm
<b>Wheel Type</b>	Never Go Flat	<b>Number of Wheels</b>	2
<b>Consumer Warranty</b>	3 Year Limited (conditions apply)	<b>AC Output</b>	230Volt/15amp
<b>Automatic Idle Control</b>	Yes	<b>DC Output</b>	12Volt/5amp
<b>Transport Handle</b>	Telescopic	<b>Alternator</b>	Permanent Magnet
<b>Hour Meter</b>	Part of Statstation	<b>Amperage</b>	10-11.3

**POWER YOU CAN RELY ON**

HEAD OFFICE: 24 Perrin Place, Salisbury QLD 4107 • PO Box 115 Archerfield QLD 4108 • ABN 40 095 032 385

**BRISBANE**

Phone: (07) 3277 8626 • Fax: (07) 3277 8627

**PERTH**

Phone: (08) 9300 6168 • Fax: (08) 9300 6471

**PORT HEDLAND**

Phone: 1300 305 912

Email: [info@genelite.com.au](mailto:info@genelite.com.au) • [www.genelite.com.au](http://www.genelite.com.au)